

SIRIUS 3RT10 3-Pole with AC Coil

Ordering Information	Coil Voltage Codes**		
<ul style="list-style-type: none"> ▶ 4-point AC Coil can be wired on top, bottom, or diagonally. ▶ Direct mount 3RU11 overload relays to create starters. ▶ Snap-on auxiliary contacts, surge suppressors, and timers. ▶ Front and side mount auxiliary contacts available on 3RT102, 3RT103, 3RT104 versions. ▶ 3RT102 9A and 12A versions have extended electrical life compared to 3RT101 versions. ▶ Overload Relays see pages 254–265. ▶ Accessories see pages 238–245. ▶ Replacement Parts see page 882. ▶ Technical Data see pages 347. ▶ Dimensions see pages 369–376. 	ACV 60Hz	ACV 50Hz	Code
	24	24	C2 [Ⓞ]
	120	110	K6
	208	208	M2
	240	220	P6
	277	—	U6
	480	—	V6
600	—	T6	
Replace the ** in the contactor catalog number with a coil code from the table above.			

Illustration	Enclosed Amp Ratings		Single-Phase HP Ratings		Three-Phase HP Ratings				Auxiliary Contacts		Screw Terminals		Cage Clamp Terminals	
	AC3	UL	115V	230V	200V	230V	460V	575V	NO	NC	Catalog No	Price \$	Catalog No	Price \$
	3RT101													
	7	20	¼	¾	1½	2	3	5	1	—	3RT1015-1A**1	55.	3RT1015-2A**1	60.
	—	—	—	—	—	—	—	—	—	1	3RT1015-1A**2		3RT1015-2A**2	
	9	20	½	1	2	3	5	7½	1	—	3RT1016-1A**1	72.	3RT1016-2A**1	77.
	—	—	—	—	—	—	—	—	—	1	3RT1016-1A**2		3RT1016-2A**2	
	12	20	½	2	3	3	7½	10	1	—	3RT1017-1A**1	89.	3RT1017-2A**1	94.
	—	—	—	—	—	—	—	—	—	1	3RT1017-1A**2		3RT1017-2A**2	
	3RT102													
	9	35	½	1	2	3	5	7½	—	—	3RT1023-1A**0	81.	3RT1023-3A**0	84.
	12	35	½	2	3	3	7½	10	—	—	3RT1024-1A**0	105.	3RT1024-3A**0	108.
	17	35	1	3	5	5	10	15	—	—	3RT1025-1A**0	121.	3RT1025-3A**0	124.
	25	35	2	3	7½	7½	15	20	—	—	3RT1026-1A**0	136.	3RT1026-3A**0	139.
3RT103														
28	35	2	5	7½	10	20	25	—	—	3RT1033-1A**0	156.	3RT1033-3A**0	159.	
32	45	2	5	10	10	25	30	—	—	3RT1034-1A**0	172.	3RT1034-3A**0	175.	
40	55	3	7½	10	15	30	40	—	—	3RT1035-1A**0	191.	3RT1035-3A**0	194.	
50	50	3	10	15	15	40	50	—	—	3RT1036-1A**0	206.	3RT1036-3A**0	209.	
3RT104														
65	90	5	15	20	25	50	60	—	—	3RT1044-1A**0	291.	3RT1044-3A**0	294.	
80	105	7½	15	25	30	60	75	—	—	3RT1045-1A**0	331.	3RT1045-3A**0	334.	
95	105	10	—	30	30	75	100	—	—	3RT1046-1A**0	453.	3RT1046-3A**0	456.	

ⓄFor 3RT101 use B0.