



SIRIUS 3RA13 Reversing Contactors with DC Coil

Ordering Information	Coil Voltage Codes**												
<ul style="list-style-type: none"> ▶ Assembled and wired reversing contactors with mechanical interlock. ▶ Contactors include control circuit wiring. ▶ Additional NO or NC auxiliary contacts can be ordered separately. ▶ Add an overload relay to create a reversing starter. ▶ Overload Relays see pages 254–265. ▶ Accessories see pages 238–245. ▶ Replacement Parts see page 882. ▶ Technical Data see pages 316–347. ▶ Dimensions see page 372. 	<table border="1"> <thead> <tr> <th>DC V</th> <th>Code</th> </tr> </thead> <tbody> <tr> <td>12</td> <td>A4[ⓐ]</td> </tr> <tr> <td>24</td> <td>B4</td> </tr> <tr> <td>48</td> <td>W4</td> </tr> <tr> <td>110</td> <td>F4</td> </tr> <tr> <td>230</td> <td>P4</td> </tr> </tbody> </table>	DC V	Code	12	A4 [ⓐ]	24	B4	48	W4	110	F4	230	P4
	DC V	Code											
	12	A4 [ⓐ]											
	24	B4											
	48	W4											
110	F4												
230	P4												
Replace the ** in the contactor catalog number with a coil code from the table above.													

Illustration	Enclosed Amp Ratings		Single-Phase HP Ratings		Three-Phase HP Ratings				Auxiliary Contacts [ⓐ]		Catalog No	Price \$
	AC3	UL	115V	230V	200V	230V	460V	575V	NO	NC		
	3RA131 (101 Frame)											
	7	20	1/4	3/4	1 1/2	2	3	5	—	2 [ⓐ]	3RA1315-8XB30-1B**	178.
	9	20	1/3	1	2	3	5	7 1/2	—	2 [ⓐ]	3RA1316-8XB30-1B**	216.
	12	20	1/2	2	3	3	7 1/2	10	—	2 [ⓐ]	3RA1317-8XB30-1B**	273.
	3RA132 (102 Frame)											
	9	35	1/3	1	2	3	5	7 1/2	—	2 [ⓐ]	3RA1323-8XB30-1B**	297.
	12	35	1/2	2	3	3	7 1/2	10	—	2 [ⓐ]	3RA1324-8XB30-1B**	352.
	17	35	1	3	5	5	10	15	—	2 [ⓐ]	3RA1325-8XB30-1B**	385.
	25	35	2	3	7 1/2	7 1/2	15	20	—	2 [ⓐ]	3RA1326-8XB30-1B**	429.
	3RA133 (103 Frame)											
	28	35	2	5	7 1/2	10	20	25	—	2 [ⓐ]	3RA1333-8XB30-1B**	530.
	32	45	2	5	10	10	25	30	—	2 [ⓐ]	3RA1334-8XB30-1B**	585.
	40	55	3	7 1/2	10	15	30	40	—	2 [ⓐ]	3RA1335-8XB30-1B**	640.
	50	50	3	10	15	15	40	50	—	2 [ⓐ]	3RA1336-8XB30-1B**	673.
	3RA134 (104 Frame)											
	65	80	5	15	20	25	50	60	—	2 [ⓐ]	3RA1344-8XB30-1B**	888.
	80	105	7 1/2	15	25	30	60	75	—	2 [ⓐ]	3RA1345-8XB30-1B**	976.
	95	105	10	—	30	30	75	100	—	2 [ⓐ]	3RA1346-8XB30-1B**	1304.

[ⓐ]For 3RA131 only.

[ⓐ]1 NC Auxiliary Contact per Contactor used for Electrical Interlock.